



0 to 1 dB Rotary Step Attenuator, 75 Ohm BNC Female To 75 Ohm BNC Female With 0.1 dB Step Rated To 1 Watt Up To 1 GHz

TECHNICAL DATA SHEET

PE7035-5

0 to 1 dB Rotary Step Attenuator, 75 Ohm BNC Female To 75 Ohm BNC Female With 0.1 dB Step Rated To 1 Watt Up To 1 GHz

Configuration

Design Step, Bidirectional Attenuator

Connector 1 BNC Female
Connector 2 BNC Female

Electrical Specifications

Frequency Range, MHz
Impedance, Ohms
75
Attenuation Value, dB
Ot o 1
Step Size, dB
Ot o 1
Step Type
Rotary
Maximum Input Power Watts

Maximum Input Power, Watts 1
Maximum VSWR 1.4:1

Frequency 1

Range, MHz DC to 500 VSWR 1.3:1 Attenuation Accuracy, dB \pm 0.07

Frequency 2

 Range, MHz
 500 to 1,000

 VSWR
 1.4:1

 Attenuation Accuracy, dB
 ± 0.07

Mechanical Specifications

Temperature

Operating Range, deg C -20 to +85

Size

 Length, in [mm]
 4.5 [114.3]

 Width, in [mm]
 4 [101.6]

 Height, in [mm]
 4 [101.6]

Connector 1

Type BNC Female

Connector 2

Type BNC Female

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 0 to 1 dB Rotary Step Attenuator, 75 Ohm BNC Female To 75 Ohm BNC Female With 0.1 dB Step Rated To 1 Watt Up To 1 GHz PE7035-5

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com





0 to 1 dB Rotary Step Attenuator, 75 Ohm BNC Female To 75 Ohm BNC Female With 0.1 dB Step Rated To 1 Watt Up To 1 GHz

TECHNICAL DATA SHEET

PE7035-5

Compliance Certifications (visit www.Pasternack.com for current document)

Plotted and Other Data

Notes:

Values at 25 °C, sea level

0 to 1 dB Rotary Step Attenuator, 75 Ohm BNC Female To 75 Ohm BNC Female With 0.1 dB Step Rated To 1 Watt Up To 1 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 0 to 1 dB Rotary Step Attenuator, 75 Ohm BNC Female To 75 Ohm BNC Female With 0.1 dB Step Rated To 1 Watt Up To 1 GHz PE7035-5

URL: http://www.pasternack.com/1db-step-bnc-female-bnc-female-1-watt-attenuator-pe7035-5-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623

Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

PE7035-5 CAD Drawing

0 to 1 dB Rotary Step Attenuator, 75 Ohm BNC Female To 75 Ohm BNC Female With 0.1 dB Step Rated To 1 Watt Up To 1 GHz

