



## N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax

### TECHNICAL DATA SHEET


**PE3W02446**

#### Configuration

- Connector 1: N Male
- Connector 2: N Male Right Angle
- Cable Type: LMR-400-UF
- Coax Flex Type: Flexible

#### Features

- Max Frequency 6 GHz
- Shielding Effectivity > 90 dB
- 85% Phase Velocity
- Double Shielded
- TPE Jacket



#### Applications

- General Purpose
- Laboratory Use

#### Description

Pasternack's PE3W02446 type N male to type N male right angle cable using LMR-400-UF coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack type N to type N cable assembly has a male to male gender configuration with 50 ohm flexible LMR-400-UF coax. The PE3W02446 type N male to type N male cable assembly operates to 6 GHz. The right angle type N interface on the LMR-400-UF cable allows for easier connections in tight spaces. The double shielding of this Pasternack cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax PE3W02446](#)



## N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax

### TECHNICAL DATA SHEET

**PE3W02446**

#### Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		6	GHz
VSWR			1.4:1	
Velocity of Propagation		85		%
RF Shielding	90			dB
Group Delay		1.2 [3.94]		ns/ft [ns/m]
Capacitance		23.9 [78.41]		pF/ft [pF/m]
Inductance		0.06 [0.2]		uH/ft [uH/m]
DC Resistance Inner Conductor		1.07 [3.51]		Ω/1000ft [Ω/Km]
DC Resistance Outer Conductor		1.65 [5.41]		Ω/1000ft [Ω/Km]
Jacket Spark			8,000	Vrms

#### Specifications by Frequency

Part Number	Length	Description	F1	F2	F3	F4	F5	Units	Weight (lbs)
		Frequency	250	500	1000	2500	6000	MHz	
PE3W02446	Custom Lengths Available	Insertion Loss (Typ.)	0.02	0.03	0.05	0.08	0.13	dB/ft	
			0.07	0.1	0.17	0.27	0.43	dB/m	
PE3W02446-12	12 inch	Insertion Loss (Typ.)	0.27	0.28	0.3	0.33	0.38	dB	0.297
PE3W02446-36	36 inch	Insertion Loss (Typ.)	0.31	0.34	0.4	0.49	0.64	dB	0.471
PE3W02446-60	60 inch	Insertion Loss (Typ.)	0.35	0.4	0.5	0.65	0.9	dB	0.645
PE3W02446-120	120 inch	Insertion Loss (Typ.)	0.45	0.55	0.75	1.05	1.55	dB	1.08
PE3W02446-300	300 inch	Insertion Loss (Typ.)	0.75	1	1.5	2.25	3.5	dB	2.385

The insertion loss data for the base model does not include loss due to the connectors. Each length includes insertion loss due to the connectors.

Loss due to Connector 1: 0.15 dB  
Loss due to Connector 2: 0.1 dB  
Base Weight: 0.297 pounds  
Additional Weight per Inch: 0.00725 pounds

#### Mechanical Specifications

##### Cable Assembly

Weight 0.297 lbs [134.72 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax PE3W02446](#)



## N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax

### TECHNICAL DATA SHEET

**PE3W02446**

#### Cable

Cable Type	LMR-400-UF
Impedance	50 Ohms
Inner Conductor Type	Stranded
Inner Conductor Material and Plating	Copper
Dielectric Type	PE (F)
Number of Shields	2
Shield Layer 1	Aluminum Tape
Shield Layer 2	Tinned Copper Braid
Jacket Material	TPE, Black
Jacket Diameter	0.405 in [10.29 mm]

One Time Minimum Bend Radius	1 in [25.4 mm]
Repeated Minimum Bend Radius	4 in [101.6 mm]
Bending Moment	0.38 lbs-ft [0.52 N-m]
Flat Plate Crush	20 lbs/in [0.36 Kg/mm]
Tensile Strength	160 lbs [72.57 Kg]

#### Connectors

Description	Connector 1	Connector 2
Type	N Male Threaded	N Male Right Angle Threaded
Specification		MIL-STD-348A
Impedance	50 Ohms	50 Ohms
Mating Cycles		500
Contact Material and Plating	Brass, Gold	Brass, Gold
Contact Plating Specification	50 $\mu$ in minimum	30 $\mu$ in minimum
Dielectric Type	PTFE	PTFE
Body Material and Plating	Brass, Tri-Metal	Brass, Tri-Metal
Body Plating Specification	150 $\mu$ in minimum	
Coupling Nut Material and Plating	Brass, Tri-Metal	Brass, Tri-Metal
Coupling Nut Plating Specification	150 $\mu$ in minimum	
Hex Size	13/16 inch	

#### Environmental Specifications

##### Temperature

Operating Range

-40 to +85 deg C

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax PE3W02446](#)



## N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax

### TECHNICAL DATA SHEET

**PE3W02446**

**Compliance Certifications** (see [product page](#) for current document)

#### Plotted and Other Data

Notes:

#### How to Order

Part Number Configuration:

**PE3W02446**- **xx****uu**

Unit of Measure:  
cm = Centimeters  
<blank> = Inches  
Length  
Base Number

Example: PE3W02446-12 = 12 inches long cable  
PE3W02446-100cm = 100 cm long cable

N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax PE3W02446](#)


URL: <https://www.pasternack.com/n-male-to-n-male-low-loss-cable-using-lmr-400-uf-pe3w02446-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE3W02446 CAD Drawing

## N Male to N Male Right Angle Low loss Cable Using LMR-400-UF Coax

ZONE	REV	DESCRIPTION	DATE	CHANGED BY	APPROVED
A		INITIAL RELEASE	11/10/2023	KGLEBOVA	AGANWANI



NOTES:

1. CABLE ASSEMBLY LENGTH LABEL PLACEMENT:  
36 INCHES OR LESS, ONE LABEL APPROXIMATELY CENTERED.  
LONGER THAN 36 INCHES, TWO LABELS APPROXIMATELY 6  
INCHES FROM EACH CONNECTOR.

2. CABLE ASSEMBLIES SHALL BE TESTED FOR CONTINUITY.
3. CABLE ASSEMBLY LENGTH DETERMINED BY ITEM PN AND DESCRIPTION.

THE INFORMATION CONTAINED IN THIS DRAWING IS THE SOLE PROPERTY OF INFINITE ELECTRONICS, INC. ANY REPRODUCTION IN PART OR WHOLE WITHOUT THE WRITTEN PERMISSION OF INFINITE ELECTRONICS, INC. IS PROHIBITED. THESE COMMODITIES, TECHNOLOGY OR SOFTWARE WERE EXPORTED FROM THE UNITED STATES IN ACCORDANCE WITH THE EXPORT ADMINISTRATION REGULATIONS. DIVERSION CONTRARY TO U.S. LAW PROHIBITED.

				INTERPRET ALL DIMENSIONS AND TOLERANCES PER ASME Y14.5	
UNLESS OTHERWISE SPECIFIED, LEADING DIMENSIONS ARE IN INCHES DIMENSIONS IN [ ] ARE MILLIMETERS				SHEET	
TOLERANCES:		SCALE		NONE	
$X = +0.05 [0.13]$		FRACTIONS		1 OF 1	
$X = +0.2 [5]$		ANGLES 1°		SHEET	
$X = +0.02 [0.5]$		$+/- 1/32$		1 OF 1	
CABLE LENGTH TOLERANCES:		ANGLES 1°		SHEET	
$X = +0.06 [1.60]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [1.50]$		$+/- 1/32$		SHEET	
$X = +0.06 [1.54]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [1.48]$		$+/- 1/32$		SHEET	
$X = +0.06 [1.20]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.60]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.50]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.48]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.30]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.20]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.10]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.05]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.03]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.02]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.01]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000000000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000000000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000000000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.00000000000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000000000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000000000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.000000000000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.000000000000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000000000000000005]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000000000000000003]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.0000000000000000000002]$		$+/- 1/32$		SHEET	
$X = +0.06 [0.0000000000000000000001]$		$+/- 1/32$		1 OF 1	
$X = +0.06 [0.00000000$					

PE3W02446 REV 1.0