



# 1.85mm Male to 1.85mm Male Cable Using RG405 Coax

## **RF Cable Assemblies Technical Data Sheet**

PE36523

## Configuration

Connector 1: 1.85mm MaleConnector 2: 1.85mm Male

• Cable Type: RG405

#### **Electrical Specifications**

Minimum	Typical	Maximum	Units
DC		40	GHz
		1.4:1	
		71.50	DC 40

#### Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	2.5	5	20	30	40	GHz
VSWR (Max.)	1.4:1	1.4:1	1.4:1	1.4:1	1.4:1	
Return Loss (Max.)	15.56	15.563	15.563	15.563	15.563	dB

## **Mechanical Specifications**

**Cable Assembly** 

Diameter 0.312 in [7.92 mm]
Weight 0.031 lbs [14.06 g]

Cable

Cable Type RG405
Impedance 50 Ohms
Inner Conductor Type Solid

Inner Conductor Material and Plating Copper Clad Steel, Silver

Dielectric Type PTFE
Number of Shields 1
Shield Layer 1 Copper

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 1.85mm Male to 1.85mm Male Cable Using RG405 Coax PE36523

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com





# 1.85mm Male to 1.85mm Male Cable Using RG405 Coax

## **RF Cable Assemblies Technical Data Sheet**

### PE36523

#### Connectors

Description	Connector 1	Connector 2	
Туре	1.85mm Male	1.85mm Male	
Impedance	50 Ohms	50 Ohms	
Contact Material and Plating	Beryllium Copper, Gold	Beryllium Copper, Gold	
Contact Plating Specification	MIL-G-45204, Type II, Class 1	MIL-G-45204, Type II, Class 1	
Coupling Nut Material and Plating	Passivated Stainless Steel	Passivated Stainless Steel	
Hex Size	5/16 in.	5/16 in.	
Torque	8 in-lbs [0.9 Nm]	8 in-lbs [0.9 Nm]	
Body Material and Plating	Stainless Steel, Gold	Stainless Steel, Gold	
Body Plating Specification	MIL-G-45204, Type II, Class 1	MIL-G-45204, Type II, Class 1	

Compliance Certifications (visit www.Pasternack.com for current document)

For RoHS Compliant version, use PE36523LF. Contact Pasternack if product cannot be found. REACH Compliant 12/19/2011

#### **Plotted and Other Data**

Notes:

· Values at 25°C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 1.85mm Male to 1.85mm Male Cable Using RG405 Coax PE36523






# 1.85mm Male to 1.85mm Male Cable Using RG405 Coax

# **RF Cable Assemblies Technical Data Sheet**

PE36523

#### **How to Order**



Example: PE36523-12 = 12 inches long cable PE36523-100cm = 100 cm long cable

1.85mm Male to 1.85mm Male Cable Using RG405 Coax from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 1.85mm Male to 1.85mm Male Cable Using RG405 Coax PE36523

URL: http://www.pasternack.com/1.85mm-male-1.85mm-male-rg405u-cable-assembly-pe36523-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

**PE36523 CAD Drawing**1.85mm Male to 1.85mm Male Cable Using RG405 Coax

