



### **RF Cable Assemblies Technical Data Sheet**


### **PE3476LF**

### **Configuration**

Connector 1: N MaleConnector 2: BNC MaleCable Type: RG223

#### **Features**

- · Max Frequency 4 GHz
- 66% Phase Velocity
- · Double Shielded
- PVC Jacket



### **Applications**

· General Purpose

· Laboratory Use

### Description

Pasternack's PE3476LF type N male to BNC male cable using RG223 coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack type N to BNC cable assembly has a male to male gender configuration with 50 ohm flexible RG223 coax. The PE3476LF type N male to BNC male cable assembly operates to 4 GHz. The double shielding of this Pasternack cable assembly provides excellent shielding effectiveness.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to BNC Male Cable Using RG223 Coax , LF Solder PE3476LF

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451





### **RF Cable Assemblies Technical Data Sheet**

### **PE3476LF**

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		4	GHz
VSWR			1.4:1	
Velocity of Propagation		66		%
Capacitance		30.8 [101.05]		pF/ft [pF/m]

<b>Specifications</b>	bv	Frequency
opcomoduono	$\sim$ y	ricquericy

opeomounement by in	944003					
Description	F1	F2	F3	F4	F5	Units
Frequency	0.1	0.25	0.5	1	4	GHz
Insertion Loss (Typ.)	0.04	0.061	0.091	0.135	0.292	dB

**Electrical Specification Notes:** 

Insertion Loss does not include the loss of the connectors. Insertion Loss is estimated as 0.1 dB per connector.

### **Mechanical Specifications**

### **Cable Assembly**

Weight 0.121 lbs [54.88 g]

Cable

Cable Type Impedance Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type Number of Shields Shield Layer 1

Shield Layer 2 Jacket Material Jacket Diameter

One Time Minimum Bend Radius

RG223 50 Ohms Solid

Copper, Silver

PΕ

Silver Plated Copper Braid Silver Plated Copper Braid

PVC, Black 0.21 in [5.33 mm]

1 in [25.4 mm]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to BNC Male Cable Using RG223 Coax, LF Solder PE3476LF





### **RF Cable Assemblies Technical Data Sheet**

### **PE3476LF**

#### **Connectors**

Description	Connector 1	Connector 2	
Туре	N Male	BNC Male	
Specification	MIL-STD-348A MIL-STD-348A		
Impedance	50 Ohms	50 Ohms	
Contact Material and Plating	Brass, Silver	Brass, Gold	
Contact Plating Specification		30μ in. minimum	
Dielectric Type	Teflon	Teflon	
Body Material and Plating	Brass, Nickel	Brass, Nickel	
Body Plating Specification		100μ in. minimum	

### **Environmental Specifications**

Temperature

Operating Range -40 to +80 deg C

Compliance Certifications (see product page for current document)

### **Plotted and Other Data**

Notes:

· Values at 25°C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to BNC Male Cable Using RG223 Coax , LF Solder PE3476LF





### **RF Cable Assemblies Technical Data Sheet**

### **PE3476LF**

#### **How to Order**

Part Number Configuration:

PE3476LF - xx uu

Unit of Measure:
cm = Centimeters
<br/>
<br/>
<br/>
<br/>
Length
Base Number

Example: PE3476LF-12 = 12 inches long cable PE3476LF-100cm = 100 cm long cable

N Male to BNC Male Cable Using RG223 Coax , LF Solder from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to BNC Male Cable Using RG223 Coax, LF Solder PE3476LF

URL: https://www.pasternack.com/n-male-bnc-male-rg223u-cable-assembly-pe3476lf-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

**PE3476LF CAD Drawing**N Male to BNC Male Cable Using RG223 Coax , LF Solder

