

N Male to N Male Cable 60 Inch Length Using RG8 Coax

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

PE3570-60 REV 1.0

1

RF Cable Assemblies Technical Data Sheet

Configuration

- Connector 1: N Male
- Connector 2: N Male
- · Cable Type: RG8

Electrical Specifications

Minimum	Typical	Maximum	Units
DC		1,000	MHz
		1.4:1	
	66		%
	30.8 [101.05]		pF/ft [pF/m]
		DC 66	DC 1,000 1.4:1 66

Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	50	100	250	500	1,000	MHz
Insertion Loss (Max.)	0.27	0.29	0.35	0.45	0.6	dB
VSWR (Max.)	1.4:1	1.4:1	1.4:1	1.4:1	1.4:1	
Return Loss (Max.)	15.56	15.563	15.563	15.563	15.563	dB

Mechanical Specifications

Cable Assembly Length Diameter	60 in [152.4 cm] 0.82 in [20.83 mm]
Weight	0.742 lbs [336.57 g]
Cable Cable Type Impedance Inner Conductor Type Inner Conductor Material and Plating Dielectric Type Number of Shields Shield Layer 1	RG8 50 Ohms Stranded Copper PE (LD) 1 Copper Braid

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable 60 Inch Length Using RG8 Coax PE3570-60

PE3570-60





N Male to N Male Cable 60 Inch Length Using RG8 Coax

RF Cable Assemblies Technical Data Sheet

Jacket Material Jacket Diameter

PVC (NC), Black 0.405 in [10.29 mm]

Connectors

Connector 1	Connector 2 N Male	
N Male		
50 Ohms	50 Ohms	
Brass, Gold	Brass, Gold	
30µ in. minimum	30µ in. minimum	
Teflon	Teflon	
Brass, Nickel	Brass, Nickel	
100 µ in. minimum	100 μ in. minimum	
Brass, Nickel	Brass, Nickel	
100µ in. minimum	100µ in. minimum	
	N Male 50 Ohms Brass, Gold 30μ in. minimum Teflon Brass, Nickel 100 μ in. minimum Brass, Nickel	

Compliance Certifications (visit www.Pasternack.com for current document) For RoHS Compliant version, use PE3570LF-60. Contact Pasternack if product cannot be found. **REACH Compliant** 12/19/2011

Plotted and Other Data

Notes:

• Values at 25°C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable 60 Inch Length Using RG8 Coax PE3570-60

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

2



PE3570-60





N Male to N Male Cable 60 Inch Length Using RG8 Coax

RF Cable Assemblies Technical Data Sheet

PE3570-60

How to Order Part Number Configuration: **PE3570** uu - XX - Unit of Measure: cm = Centimeters <blank> = Inches Length **Base Number** PE3570-12 = 12 inches long cable Example: PE3570-100cm = 100 cm long cable N Male to N Male Cable 60 Inch Length Using RG8 Coax from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry. Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable 60 Inch Length Using RG8 Coax PE3570-60 URL: http://www.pasternack.com/n-male-n-male-rg8au-cable-assembly-pe3570-60-p.aspx The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

PE3570-60 CAD Drawing N Male to N Male Cable 60 Inch Length Using RG8 Coax

