



TECHNICAL DATA SHEET


PE3C3337

Configuration

Connector 1: SMA Male
Connector 2: N Male
Cable Type: LMR-195-FR
Coax Flex Type: Flexible

Features

- Max Frequency 6 GHzShielding Effectivity > 90 dB
- 76% Phase Velocity
- · Double Shielded
- · FRPE Jacket



Applications

· General Purpose

Laboratory Use

Description

Pasternack's PE3C3337 SMA male to type N male cable using LMR-195-FR coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack SMA to type N cable assembly has a male to male gender configuration with 50 ohm flexible LMR-195-FR coax. The PE3C3337 SMA male to type N male cable assembly operates to 6 GHz. The double shielding of this Pasternack cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Fire Rated SMA Male to N Male Low Loss Cable Using LMR-195-FR Coax PE3C3337

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com





TECHNICAL DATA SHEET

PE3C3337

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		6	GHz
VSWR		JAN.	1.4:1	
Velocity of Propagation		76		%
RF Shielding	90			dB
Group Delay		1.27 [4.17]		ns/ft [ns/m]
Capacitance		25.4 [83.33]		pF/ft [pF/m]
Inductance		0.064 [0.21]		uH/ft [uH/m]
DC Resistance Inner Conductor		7.6 [24.93]		Ω/1000ft [Ω/Km]
DC Resistance Outer Conductor		4.9 [16.08]		Ω/1000ft [Ω/Km]
Jacket Spark			3,000	Vrms

Specifications by Frequency

, p = = : : : = : : : : : : : : : : : : :	10.0								
Part Number	Longth	Description	F1	F2	F3	F4	F5	Units	Weight (lbs)
Part Number	Length	Frequency	250	500	1000	2500	6000	MHz	weight (ibs)
PE3C3337	Custom Lengths	Insertion Loss (Typ.)	0.06	0.08	0.12	0.19	0.3	dB/ft	
1 2303337	Available	111361 tio11 Lo33 (1 yp.)	0.19	0.27	0.39	0.63	0.99	dB/m	
PE3C3337-12	12 inch	Insertion Loss (Typ.)	0.26	0.29	0.32	0.39	0.5	dB	0.112
PE3C3337-24	24 inch	Insertion Loss (Typ.)	0.32	0.37	0.44	0.58	0.8	dB	0.141
PE3C3337-36	36 inch	Insertion Loss (Typ.)	0.38	0.45	0.56	0.77	1.1	dB	0.169
PE3C3337-48	48 inch	Insertion Loss (Typ.)	0.43	0.53	0.67	0.96	1.4	dB	0.197
PE3C3337-60	60 inch	Insertion Loss (Typ.)	0.49	0.61	0.79	1.15	1.7	dB	0.225

The insertion loss data for the base model does not include loss due to the connectors. Each length includes insertion loss due to the connectors.

Loss due to Connector 1:

O.1 dB

Loss due to Connector 2:

0.1 dB

Base Weight:

0.112 pounds

Additional Weight per Inch:

0.00234 pounds

Mechanical Specifications

Cable Assembly

Weight 0.112 lbs [50.8 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Fire Rated SMA Male to N Male Low Loss Cable Using LMR-195-FR Coax PE3C3337

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com





TECHNICAL DATA SHEET

PE3C3337

Cable

Cable Type Impedance

Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type Number of Shields

Shield Layer 1

Chield Layer

Shield Layer 2 Jacket Material

Jacket Diameter

One Time Minimum Bend Radius Repeated Minimum Bend Radius

Bending Moment Flat Plate Crush

Tensile Strength

LMR-195-FR 50 Ohms Solid Copper

PE 2

> Aluminum Tape Tinned Copper Braid

FRPE, Black

0.195 in [4.95 mm]

0.5 in [12.7 mm] 2 in [50.8 mm] 0.2 lbs-ft [0.27 N-m] 15 lbs/in [0.27 Kg/mm]

40 lbs [18.14 Kg]

Connectors

Description	Connector 1	Connector 2 N Male Threaded		
Туре	SMA Male Threaded			
Specification	MIL-STD-348A	MIL-STD-348		
Impedance	50 Ohms	50 Ohms		
Contact Material and Plating	Brass, Gold	Brass, Silver		
Contact Plating Specification	50μ in. minimum			
Dielectric Type	PTFE	PTFE		
Body Material and Plating	Brass, Nickel	Brass, Nickel		
Body Plating Specification	100μ in. minimum			
Coupling Nut Material and Plating	Brass, Nickel	Brass, Nickel		
Coupling Nut Plating Specification	100μ in. minimum			
Hex Size	5/16 inch			
Torque	3 in-lbs [0.34 Nm]			

Environmental Specifications

Temperature

Operating Range

-40 to +85 deg C

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Fire Rated SMA Male to N Male Low Loss Cable Using LMR-195-FR Coax PE3C3337

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com





TECHNICAL DATA SHEET

PE3C3337

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order



Example: PE3C3337-12 = 12 inches long cable PE3C3337-100cm = 100 cm long cable

Fire Rated SMA Male to N Male Low Loss Cable Using LMR-195-FR Coax from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Fire Rated SMA Male to N Male Low Loss Cable Using LMR-195-FR Coax PE3C3337

URL: https://www.pasternack.com/fire-rated-sma-male-to-n-male-low-loss-cable-using-lmr-195-fr-pe3c3337-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

PE3C3337 CAD Drawing

Fire Rated SMA Male to N Male Low Loss Cable Using LMR-195-FR Coax

