

## 2.2-5 Female to N Female Low PIM Cable 36 Inch Length Using TFT-5G-402 Coax Using Times Microwave Components

#### PE3C8395-36

#### Configuration

· Connector 1: 2.2-5 Female · Connector 2: N Female • Cable Type: TFT-5G-402 · Coax Flex Type: Flexible

#### **Features**

- Max Frequency 5.8 GHz · Low PIM: -160 dBc Max • Shielding Effectivity > 80 dB
- 76% Phase Velocity · Double Shielded
- FEP Jacket

# TFT-5G-402 Center Conductor Dielectric Shield Outer Braid Jacket .160 [4.06]

#### **Applications**

- General Purpose
- · Laboratory Use

- Low PIM Applications
- Indoor and Outdoor Use
- · Plenum Rated Applications

#### **Description**

Pasternack's PE3C8395-36 2.2-5 female to type N female 36 inch cable using TFT-5G-402 coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack 2.2-5 to type N cable assembly has a female to female gender configuration with 50 ohm flexible TFT-5G-402 coax. The PE3C8395-36 2.2-5 female to type N female cable assembly operates to 5.8 GHz. Our low PIM design also offers excellent passive intermodulation performance with PIM levels better than -160 dBc. The double shielding of this Pasternack cable assembly provides excellent shielding effectiveness of better than 80 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		5.8	GHz
VSWR			1.4:1	
Velocity of Propagation		76		%
RF Shielding	80			dB
Passive Intermodulation			-160	dBc
IM3 (2x43dBm Tones) at 850 MHz or 1900 MHz				



# 2.2-5 Female to N Female Low PIM Cable36 Inch Length Using TFT-5G-402 Coax UsingTimes Microwave Components



### PE3C8395-36

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Capacitance		26.7 [87.6]		pF/ft [pF/m]

#### **Specifications by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	5.8	GHz
Insertion Loss (Typ.)	0.33	0.42	0.56	0.83	1.23	dB

**Electrical Specification Notes:** 

The Insertion Loss data above is based on the performance specifications of the coax and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1\*SQRT(FGHz) dB for the 2.2-5 connector and 0.1 dB for the N connector.

#### **Mechanical Specifications**

#### Cable Assembly

Width/Diameter 0.665 in [16.89 mm]

Cable

Cable Type TFT-5G-402
Impedance 50 Ohms
Inner Conductor Type Solid
Inner Conductor Material and Plating Copper
Dielectric Type PTFF

Inner Conductor Material and Plating

Dielectric Type

Number of Shields

Jacket Material

Copper

PTFE

2

FEP, Blue

Jacket Diameter0.16 in [4.06 mm]One Time Minimum Bend Radius0.75 in [19.05 mm]



# 2.2-5 Female to N Female Low PIM Cable36 Inch Length Using TFT-5G-402 Coax Using Times Microwave Components



### PE3C8395-36

#### **Connectors**

Description	Connector 1	Connector 2	
Туре	2.2-5 Female	N Female	
Impedance	50 Ohms	50 Ohms	
Configuration	Straight	Straight	
Mating Cycles	100	500	
Contact Material and Plating	Beryllium Copper, Silver	Phosphor Bronze, Silver	
Contact Plating Specification	200 μin	5 μm	
Dielectric Type	PTFE	PTFE	
Outer Conductor Material and Plating	Beryllium Copper, Silver	Brass, Tri-Metal	
Outer Conductor Plating Specification	100 μin	3 μm	
Body Material and Plating	Brass, Silver	Brass, Tri-Metal	
Body Plating Specification	100 μin	3 μm	
Torque	26 in-lbs 2.94 Nm	10 in-lbs 1.13 Nm	

#### **Environmental Specifications**

Operating Range Temperature

-40 to +125 deg C

Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

Notes:



# 2.2-5 Female to N Female Low PIM Cable36 Inch Length Using TFT-5G-402 Coax UsingTimes Microwave Components



#### PE3C8395-36

#### **Typical Performance Data**

#### **How to Order**

Part Number Configuration:

PE3C8395 - xx uu

Unit of Measure:
cm = Centimeters
<br/>
<br/>
<br/>
<br/>
Length
Base Number

Example: PE3C8395-12 = 12 inches long cable

PE3C8395-100cm = 100 cm long cable

2.2-5 Female to N Female Low PIM Cable 36 Inch Length Using TFT-5G-402 Coax Using Times Microwave Components from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 2.2-5 Female to N Female Low PIM Cable 36 Inch Length Using TFT-5G-402 Coax Using Times Microwave Components PE3C8395-36

URL: https://www.pasternack.com/2.2-5-female-to-n-female-low-pim-cable-36-inch-length-using-tft-5g-402-pe3c8395-36.html

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. Pasternack Enterprises reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack Enterprises does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack Enterprises does not assume liability arising out of the use of any part or document.

### PE3C8395-36 CAD Drawing

2.2-5 Female to N Female Low PIM Cable 36 Inch Length Using TFT-5G-402 Coax Using Times Microwave Components

